Printed pages: 02 Sub Code: NEC508

Paper Id: 3030 Roll No.

# B.TECH. (SEM V) THEORY EXAMINATION 2017-18 FUNDAMENTALS OF ELECTROMAGNETIC THEORY

Time: 3 Hours Total Marks: 100

**Note: 1.** Attempt all Sections. If require any missing data; then choose suitably.

#### **SECTION A**

## 1. Attempt all questions in brief.

 $2 \times 10 = 20$ 


- a) Given Vector  $\mathbf{A} = 5\mathbf{a_x} 2\mathbf{a_y} + \mathbf{a_z}$  Find the expression of a unit vector  $\mathbf{a_B}$  such that  $\mathbf{a_B}$  is parallel to Vector  $\mathbf{A}$ .
- b) Explain Faraday's Law.
- c) Define electric dipole moment.
- d) What are dielectrics? Briefly explain its types.
- e) State and explain Coulomb's inverse square law in electrostatics. What is the direction of electrical force between two point charges?
- f) What are the types of magnet? State the properties of magnetic flux lines. Use suitable diagrams if required.
- g) What is loss Tangent? Define loss angle.
- h) What is Displacement current?
- i) Write the expressions for energy stored in a magnetic field?
- i) Write the expression for transformer's EMF.

#### **SECTION B**

## 2. Attempt any *three* of the following:

 $10 \times 3 = 30$ 

a) Use spherical coordinate to find the area of part of the sphere marked 1 and 2 in figure given below. Dimensions are marked in diagram.



- b) Explain and derive the electrostatic boundary conditions for conductor–free space interface.
- c) State and explain Biot-Savart's law. Derive a relation for the force between two conductors carrying currents  $I_1$  and  $I_2$ .

- d) A uniform plane wave propagating in a medium has  $\mathbf{E} = 2e^{-\alpha z} \sin(10^8 t \beta z)$  **ay** V/m. If the medium is characterized by  $\varepsilon_r = 1$ ,  $\mu_r = 20$ , and  $\sigma = 3$  S/m, find  $\alpha$ ,  $\beta$ , and **H**.
- e) Write and explain Maxwell's equations in integral and differential form.

#### **SECTION C**

#### 3. Attempt any *two* parts of the following:

 $5 \times 2 = 10$ 

- a) State and prove Stoke's theorem.
- b) Explain Gradient, Divergence and Curl. With expression in Different Coordinate system.
- c) State & prove Divergence Theorem.

#### 4. Attempt any *one* part of the following:

 $10 \times 1 = 10$ 

- (a) Derive an expression for the electric field due to an infinite sheet carrying uniform charge of charge density  $\rho_s$  on x-y plane.
- (b) (i) An electric Field at a point P expressed in cylindrical Coordinate system is Given by  $\mathbf{E} = 6r^2 \sin \phi \, \mathbf{a_r} + 2r^2 \cos \phi \, \mathbf{a_\phi}$  Find the value of divergence of the field if the location of point P is given by (5,5,5) in Cartesian Coordinate.
  - (ii) Express **B**=10/r  $\mathbf{a_r}$  + r cose  $\mathbf{a_\theta}$  +  $\mathbf{a_\phi}$  into cylindrical co-ordinates at (5,  $\pi/2$ , -2)

# 5. Attempt any *one* part of the following:

 $10 \times 1 = 10$ 

- (a) State Ampere's circuital law. Using Ampere's circuital law, find the magnetic field intensity produced by an infinitely long filament carrying a current.
- (b) Derive a relation to determine the energy present in an assembly of charges, hence derive electrostatic energy density in joules per cubic meter.

#### 6. Attempt any *one* part of the following:

 $10 \times 1 = 10$ 

- a) Derive the expression for  $\alpha$  and  $\beta$  in a conducting medium. Explain the terms skin effect and depth of penetration.
- b) A circular loop located on  $x^2 + y^2 = 9$ , z = 0 carries a direct current of 10 A along  $a_b$ . Determine **H** at (0, 0, 4) and (0, 0, -4).

## 7. Attempt any *one* part of the following:

 $10 \times 1 = 10$ 

- (a) What is Poynting vector? Give the statement of Poynting theorem and Drive the formula for integral form of Poynting theorem and explain the physical interpretation of each term.
- (b) Consider the reflection phenomena of a plane wave travelling through a medium of permittivity  $\mathcal{E}_1$  and permeability  $\mu_1$  is incident normally to the surface of a prefect dielectric medium with permittivity  $\mathcal{E}_1$  and permeability  $\mu_2$ . Derive the expression for the reflection and transmission coefficients for the electric and magnetic fields.